



Current Equipment Type



TYPE PY83
MINIATURE
BOOSTER DIODE



B9A (Noval) Base

The BRIMAR PY83 is an indirectly heated booster diode designed for operation in A.C./D.C. television receivers. The high working peak heater to cathode potential renders the use of a separate, highly insulated heater winding unnecessary.

Heater Current	0.3 amp.
Heater Voltage	20.0 volts nom.

RATINGS

Peak Anode Current	500 mA max.
Mean Anode Current	175 mA max.
Heater-Cathode potential during flyback (heater negative with respect to cathode) †	5,000 volts max.
Peak Inverse Voltage †	5,000 volts max.

† Maximum pulse duration 15% of one cycle with a maximum of 15 μsecs.

INTER-ELECTRODE CAPACITANCES *

Anode to Cathode	6.2 pF
Heater to Cathode	2.1 pF

* Measured with no external shield.

