

### **AUX SCART Pin Connections**

The following tables identify the various pin functions associated with the AUX SCART.

#### **AUX SCART CVBS Video**

<b>PIN No</b>	<b>FUNCTION</b>
19	Composite Video Output
17	Composite Video Output return (ground)

#### **AUX SCART RGB Video**

<b>PIN No</b>	<b>FUNCTION</b>
15	Red component video output
13	Red component video return (ground)
11	Green component video output
9	Green component video return
7	Blue component video output
5	Blue component video return

#### **AUX SCART Audio**

<b>PIN No</b>	<b>FUNCTION</b>
3	Audio output (left) Mono, Left Stereo channel
1	Audio output (right) Mono, Right Stereo channel
6	Audio input (left) Mono, Left Stereo channel
2	Audio input (right) Mono, Right Stereo channel
4	Audio common return (ground)

#### **AUX SCART Control Signals**

<b>PIN No</b>	<b>FUNCTION</b>
8	0 V: DSD Standby mode
	6 V: Aspect ratio 16:9
	12 V: Aspect ratio 4:3
16	0 V: CVBS mode
	1-3 V: RGB mode
14	Return (ground)