

FBgAmp v1.1 erősítő panel

2020.01.08

db	2 db	érték	leírás	tokozás	pozíciószám	RET cikkszám	darab ár	sor-összeg	
2	4	0R1/5W	R-5W9,5X22	9,5X22-27,5	R26, R27	06-03-83	71	284	
1	2	10R/2W	R-2W4,5X11,5C	4,5X11,5-16.5	R28	03-03-38	29	58	
4	8	51R	R1/2W-10A	2,4X6,3-10A	R20, R21, R24, R25	02-00-42	5	40	
5	10	100R	R1/2W-10A	2,4X6,3-10A	R3, R9, R10, R22, R23	02-00-49	5	50	
6	12	470R	R1/2W-10A	2,4X6,3-10A	R11, R12, R13, R14, R16, R17	02-01-25	4,2	50,4	
1	2	680R	R1/2W-10A	2,4X6,3-10A	R1	02-01-44	4,6	9,2	
2	4	1k	R1/2W-10A	2,4X6,3-10A	R4, R8	02-01-63	5	20	
2	4	3k	R1/2W-10A	2,4X6,3-10A	R6, R7	02-02-15	5	20	
3	6	4k7	R1/2W-10A	2,4X6,3-10A	R15, R18, R19	02-02-39	5	30	
4	8	10k	R1/2W-10A	2,4X6,3-10A	R2, R5, R31, R32	02-02-77	4,7	37,6	
2	4	100k	R1/2W-10A	2,4X6,3-10A	R29, R30	02-03-91	4,7	18,8	
1	2	10k	TRIM13296W+Y	TR-3296W+Y	P1	08-00-26	275	550	
1	2	22p	CKER5A	KER1-5A	C2	10-01-12	13	26	
1	2	100p	CKER5A	KER1-5A	C1	10-01-20	14	28	
1	2	47n	C10,3X5,7	W103X057	C5	11-01-94	25	50	
2	4	10u/100V	ELKOD06A	D06-2,5A	C3, C4	14-05-99	25	100	
8	16	2200u	ELKOD18A	D18-7,5A	C6, C7, C8, C9, C10, C11, C12, C13	14-06-57	425	6800	
2	4	Z6V8	DZDO35-10	DO-35-10	D1, D2	20-02-09	9	36	
4	8	MBR10100G	DTO220VA	TO-220VA	D3, D4, D5, D6	19-02-99	174	1392	
1	2	LT1223	TL071	DIL08A	IC1	72-00-31	998	1996	
1	2		foglalat	DIL08		51-00-04	80	160	
2	4	BC547C	TR-NPNBC-V1	TO-92-EBC-A	T1, T3	22-02-74	21	84	
2	4	BC557C	TR-PNPBC-V1	TO-92-EBC-A	T2, T4	22-02-87	18	72	
2	4	IRFP240	M-FET-NT0247-GDS	TO-247V-GDS	T5, T7	25-05-88	480	1920	
2	4	IRFP9240	M-FET-PT0247-GDS	TO-247V-GDS	T6, T8	25-03-58	475	1900	
4	8		Csillám szigetelés			61-00-32	14	112	
1	2	IN	2-NSL25 apa	NCW254-2	CS2	53-12-44	16	32	
1	2		2-NSL25 anya			53-12-56	9	18	
1	2	segéd táp	3-NSL25 apa	NCW254-3	CS1	53-12-45	25	50	
1	2		3-NSL25 anya			53-12-57	14	28	
5	10		érintkező			53-12-55	8	80	
4	8	AC + hangszóró	CSUSZOSARU	CSUSZOSARU	CS3, CS4, CS5, CS6	65-00-92	22	176	
3	6	Mérőpontok	PADD3/1,5-A	D3/1,5	TP1, TP2, TP3	65-00-24	13	78	
1	2	Hűtőborda. Sokféle típus, és alak megfelelő lehet. A mintadarab Fischer					35-00-44	3150	6300
1	2	10x40 mm-es alumínium sínből 100 mm-es darab					?	?	
4	8	D fejű csavar M3x12					65-02-94	11	88
6	12	Alétét M3 csavarhoz					65-03-13	3	36
2	4	Hatszög távtartó külső-belső menettel M3x25					65-04-24	119	476
1	2	Hálózati transzformátor 200VA 230V/60V					?	?	
1	2	Erősítő NYÁK panel					Alkotó	1250	2500

25706

+15V segéd táp v1.1 panel (1 panelon 2 segéd táp van)

2020.01.08

db	1 db	érték	leírás	tokozás	pozíciószám	RET cikkszám	darab ár	sor-összeg	
4	4	51R	R1/2W-10A	2,4X6,3-10A	R9, R10, R11, R12	02-00-42	5	20	
4	4	180R	R1/2W-10A	2,4X6,3-10A	R1, R2, R3, R4	02-00-76	4,5	18	
4	4	6k8	R1/2W-10A	2,4X6,3-10A	R5, R6, R7, R8	02-02-58	5	20	
4	4	10u/50V(100V)	ELKOD06A	D06-2,5A	C9, C10, C11, C12	14-05-99	25	100	
4	4	100u/25V	ELKOD06A	D06-2,5A	C5, C6, C7, C8	14-07-16	26	104	
4	4	1000u/35V	ELKOD13	D13-5,0	C1, C2, C3, C4	14-05-51	193	772	
16	16	1N5819	DDO-41-10B	DO-41-10B	D1, D2, D3, D4, D5, D6, D7, D8, D9, D10, D11, D12, D13, D14, D15, D16	19-01-66	18	288	
4	4	Z15V	DZDO35-10	DO-35-10	D21, D22, D23, D24	20-00-22	10	40	
4	4	RED-3mm	LEDLED3	LED3	LD1, LD2, LD3, LD4	46-01-40	22	88	
2	2	BC547B	TR-NPNBC-V1	TO-92-EBC-A	T2, T4	22-02-65	18	36	
2	2	BC557B	TR-PNPBC-V1	TO-92-EBC-A	T1, T3	22-02-83	16	32	
2	2	BD139	TR-NPNT0126V-B	TO-126V-ECB-B	T5, T7	24-02-73	122	244	
2	2	BD140	TR-PNPT0126V-B	TO-126V-ECB-B	T6, T8	24-02-74	175	350	
2	2		biztosíték ház	PTF/15+K-3	F1, F2	51-01-42	58	116	
2	2	125 mA	olvadó betét	lomha		54-00-28	75	150	
2	2		átlátszó kupak			51-01-91	34	68	
2	2	+/- 15V	3-NSL25 apa	NCW254-3	CS2, CS3	53-12-45	25	50	
2	2		3-NSL25 anya			53-12-57	14	28	
6	6		érintkező			53-12-55	8	48	
2	2	AC230V	sorkapocs	TL308-3(2)	CS1, CS4	53-05-15	150	300	
2	2	2x15V	trafó GERT	EI38-2	TR1, TR2	57-00-26	1250	2500	
8	8	Hatszög távtartó külső-belső menettel M3x25					65-04-24	119	952
8	8	Alétét M3 csavarhoz					65-03-13	3	24
8	8	Anyá M3					65-03-08	6	48
1	1	Segéd táp NYÁK panel (2 azonos tápegység van 1 panelon)					Alkotó	1250	1250

7646